



SAFE, INTELLIGENT AND EASY TO OPERATE

APX[™] 6500 PROJECT 25 MOBILE RADIO

We've put exceptional flexibility into the advanced APX™ 6500 P25 mobile radio. We made it easy to operate and easy to use. Choose between 4 control heads, mid- and high-power models and multiple installation configurations — all of which are easy to set up. Safety features such as GPS location tracking, intelligent lighting and one-touch controls keep first responders safer than ever before.

FLEXIBLE PLATFORM

- Interchangeable control heads that best support your operational needs: 02, 03, 05, 07 and 09
- 2 transceiver options: high-power and mid-power
- Dual-control head support offered on the 02, 05, 07, 09

EASY TO SET UP AND USE

- Mid-power model fits into any existing XTL[™] footprint, so you can reuse mounting holes and cables
- High-power model trunnion design lets you remove the radio without removing the cables
- 12-character RFID label helps you track information without uninstalling your radio

CUTTING-EDGE TECHNOLOGY AND ADVANCED FEATURES

- Project 25 Phase 2 technology provides twice the voice capacity
- Integrated GPS lets you locate and track an individual or vehicle
- Advanced features like intelligent lighting, radio profiles and text messaging improve communication and coordination



APX™ 6500 SPECIFICATIONS

FEATURES AND BENEFITS:

Available in 700-800 MHz, VHF, UHF Range 1 and UHF Range 2 bands

Channels: 870*

Radio profiles Unified call list

Trunking standards supported:

- Clear or digital encrypted Trunked Operation
- Capable of SmartZone®, SmartZone Omnilink, SmartNet® Analog MDC-1200 and Digital APCO P25 Conventional System Configurations

 Narrow and wide bandwidth digital receiver
 (6.25 kHz equivalent / 12.5 kHz / 30 kHz / 25 kHz)

 Embedded digital signalling (ASTRO & ASTRO 25)

 Integrated GPS capable

 Integrated encryption hardware

 Intelligent lighting

Ships standard IP54 Utilises Windows XP, Vista and Windows 7 Customer Programming Software (CPS)

- Supports USB communications
- Built in FLASHport[™] support

Reuse of most XTL^m accessories plus new IMPRES accessories

OPTIONAL FEATURES:

Enhanced encryption software options Programming Over Project 25 (POP25) Text messaging Over the Air Rekeying (OTAR) 12-character RF ID asset tracking Tactical OTAR Siren and light interface module

Enhancement package available*

| TRANSMITTER - TYPICAL PERFORMANCE SPECIFICATIONS | | | | | | | | | | | | |
|--|------------|----------------------------|--------------------------|----------------------------|---------------------|---------------------------|---------------------|----------------------|---|----------------------|---------------------|--|
| 700 | | 700 MHz | | 800 MHz VHF | | | UHF Range 1 | | UHF Range | UHF Range 2 | | |
| Frequency Range/Bandsplits | | 764-776 MHz 794-806 MHz | | 806-824 MHz 851-870 MHz | | 136-174 MHz | | 380-470 MF | 380-470 MHz | | 450-520 MHz | |
| Channel Spacing | | 25/20/12.5 kHz | | 25/20/12.5 kHz | | 25/20/12.5 kHz | | 25/20/12.5 kHz | | 25/20/12.5 k | Hz | |
| Maximum Frequency S | Separation | Full Bandsplit | | Full Bandspl | Full Bandsplit | | Full Bandsplit | | Full Bandsplit | | | |
| Rated RF Output Power Adj* | | 10-30 Watts | | | | 10-50 Watts 25-110 Wat | | | 10-45 Watts (450-485 MHz) 10-40 Watts (485-512 MHz) 10-25 Watts (512-520 MHz) | | | |
| Frequency Stability* (-30°C to +60°C; +25°C Ref.) | | ±0.00015 % | | ±0.00015 % | | ±0.0002 % | | ±0.0002 % | | ±0.0002 % | | |
| Modulation Limiting* | | ±5 kHz / ±2.5 k | кНz | ±5 kHz/±4 k /±2.5 kHz | | | ±5 kHz / ±2. | 5 kHz | ±5 kHz / ±2.5 | kHz | | |
| Modulation Fidelity (C 12.5kHz Digital Chann | , | ±2.8 kHz | | ±2.8 kHz | | ±2.8 kHz | | ±2.8 kHz | | ±2.8 kHz | | |
| Emissions* | | Conducted+ -75/-85 dBc | Radiated+ -20/-40 dBm | Conducted -75 dBc | Radiated -20 dBm | Conducted -85 dBc | Radiated -20 dBm | Conducted -85 dBc | Radiated -20 dBm | Conducted -85 dBc | Radiated -20 dBm | |
| Audio Response* | | +1, -3 dB (EIA) | | +1, −3 dB (E | IA) | +1, −3 dB (E | IA) | +1, −3 dB (E | A) | +1, −3 dB (EIA | ۸) | |
| FM Hum & Noise 25 kHz -50 dB 12.5 kHz -48 dB | | −50 dB −48 dB | | −53 dB −52 dB | | −53 dB −50 dB | | −53 dB −50 dB | | | | |
| Audio Distortion* | | 2 % | | 2 % | | 2 % | | 2 % | | 2 % | | |

| DIMENSIONS | | | |
|---|-----------------------|------------------|----------------------|
| | | Inches | Millimeters |
| Mid Power Radio Transceiver | | 2 x 7 x 8.6 | 50.8 x 177.8 x 218.4 |
| 05 Control Head | | 2 x 7 x 2.5 | 50.8 x 180.3 x 63.5 |
| 02 Control Head | | 2.7 x 8 x 2.1 | 68.4 x 206 x 52.83 |
| 07 Control Head | | 2 x 7 x 1.5 | 50.8 x 178 x 40 |
| Mid Power Radio Transceiver and 05 Cont | rol Head–Dash Mount | 2 x 7 x 9.6 | 50.8 x 180.3 x 243.8 |
| Mid Power Radio Transceiver and O2 Cont | rol Head - Dash Mount | 2.7 x 8 x 10.5 | 68.4 x 206 x 268 |
| Mid Power Radio Transceiver and 07 Cont | rol Head - Dash Mount | 2 x 7 x 10.3 | 50.8 x 178 x 262 |
| Aid Power Radio Transceiver and Remote | Mount | 2.0 x 7 x 9.6 | 50.8 x 180.3 x 243.8 |
| igh Power Radio Transceiver | | 2.9 x 11.5 x 8.8 | 74 x 293 x 223 |
| igh Power Radio Transceiver with Handle | | 3.4 x 11.5 x 8.8 | 87 x 293 x 223 |
| Mid Power Radio Transceiver and 05 Cont | rol Head Weight | 6.6 lbs | 3.0 kg |
| Mid Power Radio Transceiver and O2 Cont | rol Head Weight | 7.12 lbs | 3.23 kg |
| Mid Power Radio Transceiver and 07 Cont | rol Head Weight | 6.74 lbs | 3.06 kg |
| High Power Radio Transceiver Weight | With Trunnion | 14.2 lbs | 6.4 kg |
| | Without Trunnion | 12 lbs | 5.4 kg |

APX 6500 CONTROL HEAD PORTFOLIO



02 RUGGED CONTROL HEAD

- Large color display with intelligent lighting
- 3 lines of text 14 characters max / 1 line of icons / 1 line of menus
- Built in 7.5 watt speaker
- Multiple control head configuration (up to 2)
- Multifunction volume/ channel knob
- Night/day mode button



03 HAND HELD CONTROL HEAD

- Large color display with intelligent lighting
- 2 lines of text14 characters max /1 line of icons /1 line of menus
- Integrated full size DTMF keypad
- Hand-held control head with intuitive user interface
- Two quick-access side buttons
- Display contrast selector



05 STANDARD CONTROL HEAD

- Tri-color display with intelligent lighting
- 2 lines of text
 14 characters max /
 1 line of icons /
 1 line of menus
- Available with Keypad Microphone
- Multiple control head configuration (up to 2)
- Display contrast selector



07 ENHANCED CONTROL HEAD

- Large color display with intelligent lighting
- 3 lines of text
 14 characters max /
 1 line of icons /
 1 line of menus
- Available with Lighting & Siren Controls or DTMF Keypad
- Multiple control head configuration (up to 2)
- Multifunction volume/ channel knob
- Night/day mode button



09 INTEGRATED CONTROL HEAD

- Extra-large full color display with intelligent lighting
- 2 lines of text 14 characters max / 1 line of icons / 1 line of menus
- Integrated full size DTMF keypad
- Large programmable one-touch buttons
- Dedicated siren controls
- Integrated Response Selector
- Night/day mode button

| RECEIVER – TYPICAL PERFORMANCE SPECIFICATIONS | | | | | | | | | | |
|--|------------------------------|------------------------|------------------------|---------------------------------|-----------------------------------|---------------------------------|----------------------------------|---------------------------------|----------------------------------|--|
| | | | 800 MHz | VHF | VHF | | UHF Range 1 | | UHF Range 2 | |
| Frequency Range/Bandsplits | | 764-776 MHz | 851-870 MHz | 136-174 MI | 136-174 MHz | | 380-470 MHz | | 450-520 MHz | |
| Channel Spacing | | 25/20/12.5 kHz | 25/20/12.5 kHz | 25/20/12.5 | 25/20/12.5 kHz | | 25/20/12.5 kHz | | 25/20/12.5 kHz | |
| Maximum Frequency | Separation | Full Bandsplit | Full Bandsplit | Full Bandsp | Full Bandsplit | | Full Bandsplit | | Full Bandsplit | |
| Audio Output Power at 3% distortion* | | 7.5 W or 15 W ++ | 7.5 W or 15 W ++ | 7.5 W or 15 | 7.5 W or 15 W ++ 7.5 W or 15 W ++ | | W ++ | 7.5 W or 15 W ++ | | |
| Frequency Stability* (-30°C to +60°C; +25°C Ref.) | | +/-0.8 PPM | +/-0.8 PPM | +/-0.8 PPN | +/-0.8 PPM | | +/-0.8 PPM | | +/-0.8 PPM | |
| Analog Sensitivity* Digital Sensitivity | 12 dB SINAD 5% BER | -121 dBm -121.5 dBm | -121 dBm -121.5 dBm | Pre-Amp -123 dBm -123 dBm | Standard -119 dBm -119 dBm | Pre-Amp -123 dBm -123 dBm | Standard -119 dBm -119 dBm | Pre-Amp -123 dBm -123 dBm | Standard -119 dBm -119 dBm | |
| Intermodulation | 25 kHz 12.5 kHz | 82 dB 82 dB | 82 dB 82 dB | 84 dB 85 dB | 86 dB 86 dB | 82 dB 83 dB | 86 dB 85 dB | 82 dB 83 dB | 86 dB 85 dB | |
| Spurious Rejection | | 91 dB | 91 dB | 95 dB | | 93 dB | | 93 dB | | |
| Audio Distortion at rated* | | 1.20% | 1.20% | 1.20% | 1.20% | | 1.20% | | 1.20% | |
| FM Hum & Noise | 25 kHz 12.5 kHz | 59 dB 50 dB | 59 dB 50 dB | 59 dB 50 dB | | 55 dB 50 dB | | 57 dB 50 dB | | |
| Selectivity* | 25 kHz 12.5 kHz 30 kHz | 85 dB 75 dB — | 85 dB 75 dB — | 85 dB 75 dB 90 dB | | 85 dB 75 dB — | | 85 dB 75 dB — | 75 dB | |

| SIGNALING (ASTRO MODE) | |
|---|---|
| Signaling Rate | 9.6 kbps |
| Digital ID Capacity | 10,000,000 Conventional / 48,000 Trunking |
| Digital Network Access Codes | 4,096 network site addresses |
| ASTRO® Digital User Group Addresses | 4,096 network site addresses |
| Project 25 — CAI Digital User Group Addresses | 65,000 Conventional / 4,094 Trunking |
| Error Correction Techniques | Golay, BCH, Reed-Solomon codes |
| Data Access Control | Slotted CSMA: Utilizes infrastructure-sourced data status bits embedded in both voice and data transmissions. |

| GPS SPECIFICATIONS | | | | | |
|----------------------|-------------------------------|--|--|--|--|
| Channels | 12 | | | | |
| Tracking Sensitivity | −153 dBm | | | | |
| Accuracy** | <10 meters (95%) | | | | |
| Cold Start | <60 seconds (95%) | | | | |
| Hot Start | <10 seconds (95%) | | | | |
| Mode of Operation | Autonomous (Non-Assisted) GPS | | | | |

| POWER AND BATTERY DRAIN | | | | | | |
|---|---|--|--|--|--|--|
| Model Type | 136-174 MHz, 380-470 MHz, 450-520 MHz, 764-870 MHz | | | | | |
| Minimum RF Power Output | 10-35 Watt (764-870 MHz), 10-50 Watts or 25-110 Watts (136-174 MHz), 10-40W or 25-110 Watts (380-470 MHz), 10-45Watts (450-485 MHz), 10-40Watts (485-512 MHz), 10-25Watts (512-520 MHz) | | | | | |
| Operation | 13.8V DC ±20% Negative Ground | | | | | |
| Standby at 13.8V | 0.85A (764-870 MHz), 0.85A (136-174 MHz), 0.85A (380-470 MHz), 0.85A (450-520 MHz) | | | | | |
| Receive Current at Rated Audio at 13.8V | 3.2A (764-870 MHz), 3.2A (136-174 MHz), 3.2A (380-470 MHz), 3.2A (450-520 MHz) | | | | | |
| Transmit Current (A) at Rated Power | 136-174 MHz (10-50 Watt) 13A (50W) 8A (15W) 764-870 MHz (10-35 Watt) 12A (50W) 8A (15W) 380-470 MHz (10-40 Watt) 11A (40W) 8A (15W) 136-174 MHz (25-110 Watt) 20A (110W) 380-470 MHz (10-40 Watt) 11A (45W) 8A (15W) 380-470 MHz (25-110 Watt) 24A (110W) | | | | | |

| MOBILE MILITARY STANDARDS 810 C, D, E, F & G | | | | | | | | | | |
|--|--------|-----------------|--------------|-------------|--------------|-------------|--------------|---------------|--------------|---------------|
| | MIL- | STD 810C | MIL-STD 810D | | MIL-STD 810E | | MIL-STD 810F | | MIL-STD 810G | |
| | Method | Proc./Cat. | Method | Proc./Cat. | Method | Proc./Cat. | Method | Proc./Cat. | Method | Proc./Cat. |
| Low Pressure | 500.1 | 1 | 500.2 | II | 500.3 | II | 500.4 | II | 500.5 | II |
| High Temperature | 501.1 | 1, 11 | 501.2 | I/A1, II/A1 | 501.3 | I/A1, II/A1 | 501.4 | I/Hot, II/Hot | 501.5 | I-A1, II |
| Low Temperature | 502.1 | I | 502.2 | I/C3, II/C1 | 502.3 | I/C3, II/C1 | 502.4 | I/C3, II/C1 | 502.5 | I-C3, II |
| Temperature Shock | 503.1 | 1 Proc | 503.2 | I/A1C3 | 503.3 | I/A1C3 | 503.4 | I | 503.5 | I-C |
| Solar Radiation | 505.1 | II | 505.2 | I | 505.3 | I | 505.4 | I | 505.5 | I-A1 |
| Rain | 506.1 | 1, 11 | 506.2 | Ι, ΙΙ | 506.3 | 1, 11 | 506.4 | 1, 111 | 506.5 | I, III |
| Humidity | 507.1 | II | 507.2 | II | 507.3 | II | 507.4 | 1 Proc | 507.5 | II-Aggravated |
| Salt Fog | 509.1 | 1 Proc | 509.2 | 1 Proc | 509.3 | 1 Proc | 509.4 | 1 Proc | 509.5 | 1 Proc |
| Blowing Dust | 510.1 | I | 510.2 | 1, 11 | 510.3 | 1, 11 | 510.4 | 1, 11 | 510.5 | I, II |
| Vibration | 514.1w | VIII/F, Curve-W | 514.3 | I/10, II/3 | 514.4 | I/10, II/3 | 514.5 | 1/24 | 514.6 | I-cat.24 |
| Shock | 516.2 | I, III, V | 516.3 | I, V, VI | 516.4 | I, V, VI | 516.5 | I, V, VI | 516.6 | I, V, VI |

| ENCRYPTION | |
|-----------------------------------|--|
| Supported Encryption Algorithms | ADP, AES, DES, DES-XL, DES-OFB, DVP-XL |
| Encryption Algorithm Capacity | 8 |
| Encryption Keys per Radio | Module capable of storing 1024 keys. Programmable for 64 Common Key Reference (CKR) or 16 Physical Identifier (PID) |
| Encryption Frame Re-sync Interval | P25 CAI 300 mSec |
| Encryption Keying | Key Loader |
| Synchronization | XL — Counter Addressing, OFB — Output Feedback |
| Vector Generator | National Institute of Standards and Technology(NIST) approved random number generator |
| Encryption Type | Digital |
| Key Storage | Tamper protected volatile or non-volatile memory |
| Key Erasure | Keyboard command and tamper detection |
| Standards | FIPS 140-2 Level 3 FIPS 197 |

| ENVIRONMENTAL SPECIFICATIONS | | | | | |
|------------------------------|---------------|--|--|--|--|
| Operating Temperature | -30°C / +60°C | | | | |
| Storage Temperature | -40°C/+85°C | | | | |
| Humidity | Per MIL-STD | | | | |
| ESD | IEC 801-2 KV | | | | |
| Water and Dust Intrusion | IP54, MIL-STD | | | | |

| FCC TYPE ACCEPTANCE ID | | | | | |
|------------------------|-----------------|-----------------------|--|--|--|
| BAND | OUTPUT Power | TRANSMITTER NUMBER | | | |
| 764-870 MHz | 10-35 Watts | AZ492FT5858 | | | |
| 136-174 MHz | 25-110 Watts | AZ492FT3821 | | | |
| 136-174 MHz | 10-50 Watts | AZ492FT3824 | | | |
| 380-470 MHz | 10-40 Watts | AZ492FT4894 | | | |
| 380-470 MHz | 25-110 Watts | AZ492FT4897 | | | |
| 450-520 MHz | 10-45 Watts | AZ492FT4896 | | | |

- Measured in the analog mode per TIA/EIA 603 under nominal conditions
 ** Accuracy specs are for long-term tracking (95th percentile values >5 satellites visible at a nominal -130 dBm signal strength)
- + Specs includes performance for the non-GNSS/GNSS bands
 ++ Output power in to 8 and 3.2 Ohm external speakers respectively

Specifications subject to change without notice. All specifications shown are typical.
Radio meets applicable regulatory requirements.

PRODUCT SPEC SHEET

APX™ 6500

| REGULATORY COMPLIANCE | | | |
|---|---|--|--|
| Padia (DRITT Astiala 2.2) | Directive 1999/5/EC RTTE EN 300 086-2 v1.3.1 | | |
| Radio (R&TTE Article 3.2) | EN 300 113-2 v1.5.1 | | |
| | EN 301 489-1 V1.9.2 | | |
| EMC (R&TTE Article 3.1.b) | EN 301 489-5 V1.3.1 | | |
| | EN 300 086-2 v1.3.1 (rad. emissions) | | |
| Electrical Safety (R&TTE Article 3.1.a) | EN 60950-1:2006 +A11:2009 +A1:2010 +A12:2011 + AC:2011 | | |
| Electrical Safety (natre Article 5.1.d) | ICNIRP(1998) Occupational Controlled Environment | | |
| Fnvironmental | Directive 2002/96/EC WEEE | | |
| Environmental | Directive 2011/65/EU RoHS-2 | | |
| Year of first application of CE Mark | 2012 (136-174MHz) ; 2012 (380-470MHz) | | |
| Type Designator | MMB305P (136-174MHz) ; MMB505P (380-470MHz) | | |
| Automotive | E-mark, 72/245/EEC and 2004/104/EC as amended by 2009/19/EC | | |
| Automotive Marking | e 24 03 2044 | | |

Motorola Solutions UK Limited, Jays Close, Viables Industrial Estate, Basingstoke, Hampshire RG22 4PD **motorolasolutions.com**MOTOROLA, MOTO, MOTOROLA SOLUTIONS and the Stylised M Logo are trademarks or registered trademarks of Motorola Trademark Holdings, LLC and are used under license. All other trademarks are the property of their respective owners. © 2015 Motorola Solutions, Inc. All rights reserved.



