

L6Q pole tap accessory

For quick and easy power to the Motorola Solutions L6Q license plate recognition camera, just twist and lock this advanced OWL Power Tap on any 120VAC - 277VAC streetlight. The patented design of this power tap will supply 12V DC directly to the L6Q LPR camera through a 35 foot cable and pre-wired M12 connector.

Features

- Eliminates luminaire wiring
- Simple plug-in twist lock installation
- 7-pin Power Tap works with any photocontrol
- Pass-through photocontrol operations
- Input voltage: 120 / 208 / 240 / 277 VAC
- Output voltage: 12 Vdc
- Cable: 35' cable with Motorola M12 connector

SPECIFICATIONS

IEEE Standards	Conforms to ANSI C136.14
Housing	UV stabilized impact resistant polycarbonate, color gray
Temperature	-40° to +70° C, -40° F to +158° F
DC Power Cable	12Vdc
Power	20W (with De-rating)
MSI Part Number	VSQ-60-341, VS-L6Q-POLE-PWR-TAP

To learn more, visit:

www.motorolasolutions.com



Motorola Solutions, Inc. 500 West Monroe Street, Chicago, IL 60661 U.S.A. motorolasolutions.com
Specifications are subject to change.

MOTOROLA, MOTO, MOTOROLA SOLUTIONS and the Stylized M Logo are trademarks or registered trademarks of Motorola Trademark Holdings, LLC and are used under license. All other trademarks are the property of their respective owners. ©2024 Motorola Solutions, Inc. All rights reserved. 03-2024 [CK03]

